

PBA Design-for-eXcellence Guideline

EDM-D-010
Power Integrity

V1.0
March 2015

Contact

Geert Willems

Phone: +32 16 288962
Mobile: +32 498 919464
Geert.Willems@imec.be
IMEC
Kapeldreef 75
B3001 Heverlee

Davy Pissoort

Phone: +32 59 569039
Davy.Pissoort@kuleuven.be
KU Leuven
Technologiecampus Oostende

Verantwoordelijke uitgevers

Luc Van den Hove - IMEC

Copyright © imec 2015 All rights reserved.

Only an authorized person is hereby permitted to view and use this document subject to the following conditions:

1. This document may be used for informational purposes only.
2. Any copy of this document or portion thereof must include the copyright notice.
3. This information is provided "AS IS" and without warranty of any kind, express, implied, statutory, or otherwise.
4. Imec shall not be liable for any actual, direct, indirect, incidental or consequential damages arising out of the use, performance or application of this document.

Permission is not granted for resale or commercial distribution or use of the document, in whole or in part, or by itself or incorporated in another work.

The Electronics Design and Manufacturing Guidelines principles

The PBA Design-for-eXcellence (DfX) Guidelines are designed to provide all electronic supply chain actors involved in the design, qualification, industrialization and production of Printed Board Assemblies practical guidelines to master the multi-disciplinary hardware aspects of electronic module realization and operation in a cost-effective way. The PBA DfX Guidelines are not electrical design guidelines. The PBA DfX guidelines provide the electrical designer the boundary conditions of industrial electronic manufacturing technology and basic operational reliability. It is intended to support the development of cost-effective, reliable PBA with a short time-to-market requiring a minimum number of design iterations.

Some of the characteristics of the PBA DfX Guidelines are:

- The PBA DfX Guidelines are oriented towards the overall optimization of the hardware realization aspects of the final PBA based product.
- The guidelines refer to the relevant industry standards that are predominantly used in the international electronics industry such as those published by organizations as IPC and JEDEC. The guidelines do not replace industrial standards but define or recommend what options in the standards to use and will fill-in gaps if necessary. They provide the basis on which a company/product/product-line or application specific approach for design, industrialization and/or realization can be defined.
- Scientific argumentation and physical models form the basis of a large part of the guidelines and of the associated tools. This allows the use of the guidelines beyond the boundary of the users' experience domain. Therefore, it provides a powerful product and process innovation aid.
- The PBA DfX Guidelines will not specify, recommend or exclude specific brands of materials, components, suppliers or products. They will put forward minimal requirements on quality, physical and chemical properties and testing. They define and provide the DfManufacturing window for PBA realization.
- The PBA DfX Guidelines are based on verifiable physical models, standards and empirical data.

PBA DfM Guideline Scope

- This guideline focusses on the Power Integrity (PI) of a PBA. This guideline is complementary to the EMC guideline EDM-I-003 and the SI guideline EDM-D-009.
- This Power Integrity guideline provides a concise overview of a generic work-flow to obtain a low-impedance power distribution network on a PBA
- This guideline applies to all types (rigid, flex, flex-rigid) and classes (IPC 1, 2 and 3) of PCB and PBA, both SnPb and leadfree soldered.

Acknowledgement

This document was realized in collaboration with the industrial and academic partners of imec's Center of Electronics Design & Manufacturing and Sirris.

Funding organizations

IWT is acknowledged for funding the VIS projects - especially the Collective Research project CO-PBA-DfX and the VIS-traject PROSPERITA - that have provided the scientific background for the PBA DfM Guidelines and gained the necessary industry support. For the EMC, SI and PI guidelines, IWT is acknowledged for funding the IWT Tetra Project DfXBridge.

imec contributors

Geert Willems, Ph.D.

KU Leuven contributors

Davy Pissoort, Ph.D.
Bart Boesman

Contributing cEDM partners

Barco, Kortrijk

Table of Contents

The Electronics Design and Manufacturing Guidelines principles.....	2
PBA DfM Guideline Scope	2
Acknowledgement.....	3
1. Applicable Documents	5
2. Applicability of the PBA DfX Guideline EDM-D-010.....	5
3. Power Integrity	5
3.1. Design-for-Power Integrity goal and approach.....	5
3.2. Specifying the target impedance	6
3.3. Decoupling the PDN.....	6
3.3.1. Step 1: VRM (DC → ~2kHz) and bulk capacitors (~2kHz → ~1MHz).....	7
3.3.2. Step 2: Decoupling with HF capacitors (1MHz ->~100MHz).....	8
3.3.3. Decoupling with On-Package and On-Die capacitors.....	13
4. Revisions	14
Appendix A:	15
A.1. Bandwidth of a signal and highest frequency of concern.....	15
A.2 High-speed signals	15
Appendix B	16
B.1 The multilayer ceramic capacitor: typical ESL and ESR values.....	16
Equivalent series inductance (ESL)	16
Equivalent Series Resistance (ESR).....	17
B.2. Plane-pair impedance: analytical model.....	18

1. Applicable Documents

This PBA DfM Guideline refers as part of the guideline to the most recent versions of the following documents and standards including their amendments.

EDM-I-003 EMC Integration Guideline
EDM-D-009 Signal Integrity Design Guideline

2. Applicability of the PBA DfX Guideline EDM-D-010

- The recommendations given in the guideline are intended to help the user in making choices that improve the manufacturability, reliability, testability, etc., of the final PBA. These recommendations are of a generic nature. Therefore, in specific cases more optimal solutions may exist.
- Design specification takes precedence over this guideline.

3. Power Integrity

3.1. Design-for-Power Integrity goal and approach

- 3.1.1. Design for Power Integrity ensures that each component receives a constant power supply voltage by minimizing noise caused by the fast current changes of switching components that connect to the PDN. It aims at keeping high-frequency currents caused by fast-switching components close to these components.
- 3.1.2. Improper Design for Power Integrity leads to:
 - 3.1.2.1. Ground bounce or Simultaneous Switching Noise
 - 3.1.2.2. Eye diagram collapse (see Signal Integrity)
 - 3.1.2.3. Unwanted radiation from e.g. cables connected to the PBA (see EMC)
- 3.1.3. Power Integrity is achieved by appropriate design of the Power Distribution Network (PDN) of the PBA. Based on application-specific requirements, the impedance of the PDN has to be lower than a target value from DC up to the highest-frequency-of-concern on the PBA as defined in Appendix A.
- 3.1.4. The first step is to specify the target impedance for each voltage rail.
- 3.1.5. The second step is to optimize the PDN by applying a good Voltage Regulator Module (VRM) together with a well-thought decoupling strategy on the PBA. Components especially designed for high-frequencies and mounted in the appropriate way form the basis of a successful decoupling strategy.
- 3.1.6. This guideline provides analytical formulas which can be used as first order estimates in the design of a PDN. To obtain a well-optimized PDN simulation based verification and optimization is required.